


NEW



A2120D

REMOTELINK™ Mains Powered Amplifiers

- Mains powered amps for bigger systems, longer cable runs
- Fully screened with F-Type connectors and LED indicator
- Watch and change SKY™ channels in up to 12 extra rooms
- Compatible with ME100 and ME200 RemoteLink IR sensor

PRODUCT RANGE

- A120D - 2 room amplifier
- A240D - 2-in, 4 room amplifier
- A260D - 2-in, 6 room amplifier
- A280D - 2-in, 8 room amplifier
- A2120D - 2-in, 12 room amplifier

TECHNICAL SPECIFICATION

	A120D	A240D	A260D	A280D	A2120D
No. of Inputs	1	2	2	2	2
No. of Outputs	2	4	6	8	12
Frequency Range	45-862MHz	45-230/470-862MHz	45-230/470-862MHz	45-230/470-862MHz	45-230/470-862MHz
Gain	8dB±2	8dB±2	8dB±2	8dB±2	8dB±2
Noise Max	<3.5dB	<3.5dB	<3.5dB	<3.5dB	<3.5dB
Max. Output*	78dBµV	78dBµV	78dBµV	78dBµV	78dBµV
Isolation Between Outputs	>20dB	>20dB	>20dB	>20dB	20dB
Return Path Frequency	5-30MHz	5-30MHz	5-30MHz	5-30MHz	5-30MHz
Impedance		75Ω			
Mains Power (Red LED)	230V AC ± 10% 50Hz Fitted Mains Plug BS1363 3A rating				

* DIN 45004B 3 carriers, IMD₃ - 60dB