

TMS 5x32 C EB

Art. Number 318630





Cascade multiswitch for 1 Satellite position with 5 inputs and 5 trunk outputs, suitable for distributing satellite and terrestrial signals in small to large sized systems. Available with 32 subscriber outputs and powered by the TMS PSU external power supply either directly or via the SAT trunk lines.

Dependability guaranteed: a 6-year warranty is our guarantee that TRIAX's core values of reliability and innovation are the foundation of our new multiswitches.

European IRS Certification Scheme: TMS 5 Input Cascade Multiswitches and Amplifiers are certified to the EICS scheme, demonstrating the high quality of the solution and compatibility with all major satellite and TV platforms.

The TMS 5x32 C EB offers excellent performance and flexibility, with a compact design for installations even in confined spaces.

Excellent performance

- Low insertion loss
- High isolation
- Low power consumption
- RED compliant
- ESD Protection

Flexibility

All the functionality you need in a simplified, streamlined range:

- Easier to select the right product
- Fewer products to stock
- Active/Passive Terrestrial Switch

Convenience

Designed with installer convenience in mind:

- Equidistant F-connectors on all multiswitches
- Colour-coded input labels
- LED power indicator
- Flexible power injection
- Earth bars

Technical Specifications

ORDER INFORMATION

EAN Number 5702663186309

CHARACTERISTICS

LNB type	Quattro
Max. input level - SAT (IMD3 - 35dB) dBμV	99 dBμV
Max. input level - TER (IMD3 - 60dB) dBμV	90 dBμV
Max. output level SAT @ -35 dB IMD3 dBμV	100 dBμV
Max. output level TER @ -60dB IMD3 dBμV	90 dBμV
LNB current max. mA	3000 mA
Switch commands	DiSEqC 1.0/2.0, 13/18V, 0/22kHz



Technical Specifications

FREQUENCY RANGE

Frequency range TER MHz	Active: 47...862 / Passive: 5...862 MHz
Frequency range SAT MHz	950...2200 MHz

GAIN

Gain - SAT (with 5 dB slope) dB	-4...+1 ± 2 dB
Gain - TER dB	0 ± 2 dB

LOSS

Tap loss TER dB	33 ± 2 dB
Insertion loss - trunkline SAT dB	7 ± 1 dB
Insertion loss - trunkline TER dB	5 ± 1 dB

ISOLATION

Isolation SAT to TER dB	> 30 dB
Isolation trunk to trunk dB	> 30 dB
Isolation cross polarisation H/V dB	30 dB
Isolation out-out SAT dB	30 dB
Isolation out-out TER dB	25 dB

RETURN LOSS

Return loss SAT inputs dB	>10 dB
Return loss SAT outputs dB	>10 dB
Return loss TER inputs dB	>10 dB
Return loss TER outputs dB	>10 dB
Return loss TAP outputs dB	10 dB

ELECTRICAL

Impedance Ω	75 Ω
----------------------	-------------

OPERATIONAL

LINE power DC voltage (max.) VDC	15...20 VDC
LINE power current (max.) mA	2000 mA
PSU output DC voltage VDC	18 VDC
ESD protection	4KV inputs & sub outputs
DC Current consumption mA	30mA TER passive mA 200mA TER active
PSU/adaptor Art number	318165, 318166, 318167
Max. current to each output (supplied by set top)	<50 mA
Control LEDs	Green LED (Power)
Temperature - operating °C	-20...+55 °C

CONNECTORS

Connector Type	F-female
Connector DC	F-female
Number of trunk inputs	4 SAT, 1 TER



Technical Specifications

Number of trunk outputs	4 SAT, 1 TER
Subscriber outputs	32
Colorcoding @IF/TER inputs	VL=Black, VH=Red, HL=Green, HH=Yellow, White=TER

MECHANICAL

Main material	Steel housing
Packing QTY	1
Product Height mm	280 mm
Product Width mm	140 mm
Product Depth mm	65 mm
Packaging Height m	0.070 m
Packaging Width m	0.270 m
Packaging Depth m	0.205 m
Packaging Volume m3	0.000 m3
Net Weight kg	1.412 kg
Tara Weight kg	0.190 kg
Total Weight kg	1.602 kg
Remarks	Earth bars